

# Proprietary LoRa receivers

## Modbus Receiver - TCP/IP & RTU

RX MODBUS 500-502



- Can handle 50 Enless sensors
- Converts received data into Modbus table
- TCP/IP and RTU communication
- Facilitates integration of Enless sensors into the BMS
- Power supply 7.5 - 24VDC

### Technical Specifications

#### Physical Characteristics

Protection rating	NEMA 2 / IP60
Mounting	Wall / Clamp / DIN rail
Operating temperature	-20 / +55°C
Operating relative humidity	20 - 80% (non-condensing)
Operating altitude	< 2000m
Power supply	External 7.5 to 24VDC 1A Max (typ. 12V 1A)

#### Radio

Radio antenna	Antenna not provided (SMA connector) Use of ANT REN SMA LR 1000-008 antenna recommended
Supported protocol	Enless LoRa mode
Frequency	US915

## Configuration

Receiver server	Pairing of sensors Analysis of RSSI levels Visualization of Modbus table
Modbus	Possible configuration of sensors from the receiver's Modbus table

## Communication with the BMS

Modbus	
Connection	TCP/IP or RTU RS485 / RS232
TCP client	One TCP client at a time

## Certifications



## Dimensions (mm)

